



MPCOID21X

MODULE PORT CONVERTER
for the use of a second input module at the D21x series

The standard version of the D21x series of DoorBird IP Video Door Stations offers two ports: one for the connection of input modules (red), e.g. keypad or multi-user modules, and the other one for the connection of output modules (green), e.g. display or info modules.

The Module Port Converter offers the possibility to convert the port for output modules (green) into another port for input modules (red), e.g. to operate a keypad and a multi-user module simultaneously.

When using the Module Port Converter, it is not possible to use output modules on the port.

The Module Port Converter can be used for the following combinations.

Combination A:

Port (red): Keypad module with 12 keys or Fingerprint Reader Module 50

Port (green) with Module Port Converter: MTM14A or MTM18A

Combination B:

Port (red): MTM14A or MTM18A

Port (green) with Module Port Converter: Keypad module with 12 keys or Fingerprint Reader Module 50

Combination C:

Port (red): Keypad module with 12 keys

Port (green) with Module Port Converter: Fingerprint Reader Module 50

Combination D:

Port (red): Fingerprint Reader Module 50

Port (green) with Module Port Converter: Keypad module with 12 keys

GENERAL

Dimensions	5 x 30 x 15 mm (H x W x D) 0.04 x 1.18 x 0.59 in (H x W x D)
Connectors	<ul style="list-style-type: none"> • Incoming port for connection of the green cable of the D21x series • Outgoing red cable for connection of another input module
Scope of delivery	1x Module Port Converter MPCOID21X
Approvals	IP40
Weather-proof	No
Weight	5 g
EAN	4260423868670

CURRENT SYSTEM REQUIREMENTS

Supported door stations	D21x series with free port for an output device module (green cable)
-------------------------	--

OPTIONAL ACCESSORIES

Sold separately	see www.doorbird.com/buy
-----------------	--