



## CALL BUTTONS

### D2100E & D2100EA

### D1100E



[Illuminated Call Button  
for DoorBird D21x](#)




#### Connection options:

- A. One call button connected to the port for one call button (yellow) of the main unit
- B. 2-18 call buttons connected to the Multi-Tenant Module "MTM18A"
- C. 2-56 call buttons connected to the Multi-Tenant Module "MTM56A"



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



[Illuminated Call Button  
for DoorBird D11x](#)



Not compatible



#### Connection option:

1-2 call buttons connected to the port for call buttons (CB) of the main unit



[Illuminated stainless  
steel button for DoorBird  
D1101KH Classic](#)



[Illuminated stainless steel  
button for DoorBird D21x](#)



#### Connection options:

- A. One call button connected to the port for one call button (yellow) of the main unit
- B. 2-18 call buttons connected to the Multi-Tenant Module "MTM18A"
- C. 2-56 call buttons connected to the Multi-Tenant Module "MTM56A"



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



[Illuminated stainless steel  
call button with separate  
backlit nameplate for  
DoorBird D21x](#)

## SPARE PARTS



[Multi-Tenant Module  
MTM18A](#)

#### Connection option:

One Multi-Tenant Module connected to the port for input modules (red) of the main unit



**Only one Multi-Tenant module can be connected to the main unit.**



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



[Multi-Tenant Module  
MTM14E](#)



[Multi-Tenant Module  
MTM56A](#)



[Module Port Converter  
MPCOID21 for connecting a  
second input module on the  
D21x series](#)



#### Connection option:

One Module Port Converter connected to the port for output modules (green) of the main unit



Not compatible

# ENGINEERING EDITIONS FOR INTEGRATION PURPOSES COMPATIBILITY OVERVIEW



## SPARE PARTS

## D2100E & D2100EA

## D1100E



[Fingerprint Reader Module 50](#)



### Available combinations:

- A. One Fingerprint Reader Module connected to the port for input modules (red) for devices with one call button attached to the main unit
- B. One Fingerprint Reader Module connected to the port for output modules (green) with the Module Port Converter "MPCOID21" for devices with Multi-Tenant modules attached to the main unit

### Connection option:



One Fingerprint Reader Module connected to the port for add-on modules (COM) of the main unit

**Not compatible with Multi-Tenant Modules or Keypad-Modules**



[Keypad Module with 12 stainless steel keys](#)



### Available combinations:

- A. One Keypad Module connected to the port for input modules (red) for devices with one call button attached to the main unit
- B. One Keypad Module connected to the port for output modules (green) with the Module Port Converter "MPCOID21" for devices with Multi-Tenant modules attached to the main unit

### Connection option:



One Keypad Module connected to the port for add-on modules (COM) of the main unit

**Not compatible with Multi-Tenant Modules, Fingerprint Reader Module 50 or other Keypads**



[Keypad Module with 12 keys](#)



Not compatible

### Connection option:



One Keypad Module connected to the port for add-on modules (COM) of the main unit

**Not compatible with Multi-Tenant Modules, Fingerprint Reader Module 50 or other Keypads**



[Keypad Module with 16 stainless steel keys for DoorBird D21DKx](#)



### Connection option:

- One Keypad Module connected to the port for input modules (red) of the main unit
- Can only be used in combination with a Display Module.**



Not compatible



[Display Module, Color, 3.5 inch, for DoorBird D21DKx](#)



### Connection option:

- One Display Module connected to the port for output modules (green) of the main unit
- Can only be used in combination with a Keypad Module with 16 keys.**



Not compatible



[Info Module for DoorBird D21x](#)



### Connection option:

- One Info Module connected to the port for output modules (green) of the main unit



Not compatible