



**MTM56A**

## MULTI-TENANT MODULE

For connecting up to 56 DoorBird call buttons

GENERAL	
Dimensions	125 x 74 x 34,5 mm (H x W x D) 4.92 x 2.91 x 1.36 in (H x W x D)
Connectors	<ul style="list-style-type: none"> <li>• 56 jacks for up to 56 original call buttons</li> <li>• Screw terminal for 12 - 48 V DC, 1.5 A, for power supply of the call buttons</li> <li>• For connecting with the door station series D21x: Connect with red cable of the door station</li> </ul>
Scope of delivery	1x Multi-Tenant Module MTM56A 1x Power supply unit (main adaptor) with four country-specific adaptors (100 - 240 V AC to 15 V DC) 1x Small Parts
Approvals	IP40
Weather-proof	No
Weight	100 g
EAN	4260423868687
CURRENT SYSTEM REQUIREMENTS	
Supported door stations	D21x series with maximum one additional input device module
OPTIONAL ACCESSORIES	
Sold separately	see <a href="http://www.doorbird.com/buy">www.doorbird.com/buy</a>

The Multi-Tenant Module for the D21x IP Video Door Station enables the connection of up to 56 DoorBird call buttons.

Contrary to the MTM14E and MTM18A, the power supply is not provided centrally via the Door Station but via a separate connector using 12 - 48 V DC. The multi-tenant module comes with a plug-in power supply (110 - 240 V AC to 15 V DC) with 4 country adapters.

